Anthem MRX 540 8K

AV-receivers



Technische specificaties

Merk	Anthem
Model	MRX 540 8K
Productcategorie	AV-receivers
Analoge ingangen	5 In
Luidsprekerimpedantie	>4Ω
Kanalen	7.2
Maximale luidsprekeropstelling	5.2.2
Ruimtecorrectie	Ja
Hires-audio	Yes - FLAC, ALAC, WAV, DSD
HDMI-versie	HDMI 2.1
Netwerk (LAN)	Ja
Digitale ingangen (Coax)	2 In
Digitale ingangen (Optical)	3 In / 1 Out

Technische specificaties

Display voorzijde	6" TFT
Constructie	Aluminum Chasis with Machine Aluminum Faceplate
Afmetingen (W)	17" (43.18 cm)
Afmetingen (D)	14-1/2" (36.4 cm)
Afmetingen (H)	6" (15.24 cm)
Hoogte met rackmontage	4U
Verbruik bij typische belasting	365 W
Verbruik in stand-by	0.3 W
Stand-byverbruik met IP-bediening	1.8 W
Uitvoering 120 V	In countries where the line voltage is 120 V, this product operates from a single phase AC power source that supplies between 108 V and 132 V at a frequency of 60 Hz.
Uitvoering 220-240 V	In countries where the line voltage is 220, 230, or 240 V, this product operates from a single phase AC power source that supplies between 198 V and 264 V at a frequency of 50 Hz.
Gewicht	28.2 lb (12.8 kg)